



#### **Anchor Bolt Retrofit Adapter** Plate -

Fits most existing 3-Bolt or 4-Bolt Patterns



**Bollard Mounting** 

Cover Plate -Allows mounting of Bollard using the bollard cast aluminum base plate

Allows for retrofit of **ALL Jemm Bollards** to most EXISTING anchor bolt patterns.



# BREBASE Bollard Retrofit Base Kit

The BBASE Bollard Retrofit Base Kit allows installation of new bollards to most existing bolt patterns without removal of existing bolts. Fits all LEPG bollards, both round and square.

## **ALL Round JEMM Bollards**




#### **Anchor Bolt Retrofit** Adapter Plate -

Mounts to existing anchor bolts



using Bollard base cast aluminum base plate (Hardware Included)



## **ALL Square JEMM Bollards**



See Pages 2 and 3 for Specifications, Installation **Guide, and Mounting Details.** 

## Order Information Example:

**Cover Plate** 

Adapter Plate

**BREBASEZ** 


Model	Color
BBASE=Bollard Retrofit Base Kit	B=Black Z=Bronze C=Custom

(Consult Factory)

Project Name:	Fixture Type:
Complete Catalog #:	Date:
Comments:	

# Jemm LIGHTING

## Anchor Bolt Retrofit Adapter Plate



## Dimensions

Diameter (D)

10¾" (271mm)

Height (A)

1" (26mm)



## **Bollard Mounting Cover Plate**




Plate has threaded holes in patterns for each LEPG bollard size. Mounting bolts are included. Bollard base mounts to plate.


> Plate includes 4 set screws on sides at 90 degrees for locking base cover to mounting plate. Fully rotatable.

### **Dimensions**


Diameter (D) Height (A)

11½" (292mm) 1½" (38mm)

## Anchor Bolt Retrofit Adapter Plate allows for



6.5" bolt circle for Drilled Anchors. Used when existing anchor bolts do not fit 4-bolt or 3-bolt slots or are damaged. These must be cut off and new drilled anchors installed.



# **BBASE** Bollard Retrofit Base Kit

#### **Bollard Retrofit Base Kit includes:**

Heavy duty die cast aluminum Anchor Bolt Retrofit Adaptor Plate


- Includes slots for existing anchor bolt mounting, 3@120°, 4@90° or 2@ 180° (3.5" to 5" diameter bolt circle). Slots can accommodate ½" to ¾" diameter anchor bolts.
- Includes large diameter slots for installing field drilled anchors (not included) in the event that the existing anchor bolt pattern does not fit slots, or anchor bolts are damaged or unusable.
- Includes 4 Stainless Steel leveling bolts with two leveling bubbles at 90° to level base prior to mounting new bollard.
- Center conduit entrance hole designed to accommodate two <sup>3</sup>/<sub>4</sub>" PVC conduits.


Heavy duty die cast aluminum Bollard Mounting Cover Plate

- Includes threaded holes in patterns to match ALL JEMM bollard base mounting plates.
- Stainless Steel bolts for mounting bollard base plate.
- •4 Stainless Steel set screws at 90° for securing the cover plate to the adaptor plate. Cover plate can be rotated 360°.

Powdercoat finish over chromate conversion coating in Black or Bronze standard to match JEMM Bollards.

## Anchor Bolt Retrofit Adapter Plate Bolt Circles for use with existing anchor bolts.





For use with 3 bolts @ 120°



# **BBASE** Bollard Retrofit Base Kit

**BBASE Template:** 

